



## SC-Cmusic

### FEATURES

- Professional DMX controllable amplifier, enables to set up DMX initializing address.
  - \* Amplifier on / off unit.
  - \* Amplifier volume adjusts.
  - \* Select input audio source (Aux or Mp3).
  - \* Mute the amplifier.
  - \* MP 3 Folder.
  - \* Select Song.
  - \* FM-Radio.
  - \* Play / Stop.
  - \* Next / PRV.
- 20W amplifier, its stereo output is able to directly drive external speaker.
- AUX Input / LINE Out optional.
- Built-in MP3 player.
  - Allows to transmit and save music folders via USB or MICRO SD,
- External infrared remote controller available.
- Power failure protection.

### SPECIFICATION

<input type="checkbox"/> POWER OPERATOR	24VDC , 30W.
<input type="checkbox"/> DC IN	4Pin terminal socket
<input type="checkbox"/> DMX IN	3Pin terminal socket
<input type="checkbox"/> AUDIO OUTPUT	4Pin terminal socket
<input type="checkbox"/> DRIVER	SC-TOUCH 16 L
<input type="checkbox"/> CONTROL PROTOCOL	DMX-512 (1990)
<input type="checkbox"/> LISTING	CE certified
<input type="checkbox"/> HOUSING	Black Polycarbonate (White, Gray optional)
<input type="checkbox"/> OPERATING TEMPERATURE	0 °C ~ +35 °C
<input type="checkbox"/> STORAGE TEMPERATURE	-20 °C ~ +70 °C
<input type="checkbox"/> DIMENSIONS	195(L) x 105(W) x 18(H)mm
<input type="checkbox"/> WEIGHT	230g

### DIMENSIONS

